SUPER POKER

V305US

SW1	LEVEL	1	2	3	4	5	6	7	8
HOLD MODE	HOLD WIN	OFF							
	AUTO HOLD	ON							
MAX PLAY	8		OFF	OFF					
	10		ON	OFF					
	50		OFF	ON					
	100		ON	ON					
MIN. PLAY	1				OFF	OFF			
	5				ON	OFF			
	10				OFF	ON			
	20				ON	ON			
TICEKT PAYOUT	OFF						OFF		
	ON						ON		
PAYOUT MODE	MANUAL							OFF	
	AUTO							ON	
SYSTEM LIMIT	OFF								OFF
	ON								ON

SW2	LEVEL	1	2	3	4	5	6	7	8
MAIN RATE	50%	OFF	OFF	OFF					
	60%	ON	OFF	OFF					
	65%	OFF	ON	OFF					
	70%	ON	ON	OFF					
	75%	OFF	OFF	ON					
	80%	ON	OFF	ON					
	85%	OFF	ON	ON					
	90%	ON	ON	ON					
W-UP RATE	75%				OFF	OFF			
	80%				ON	OFF			
	85%				OFF	ON			
	90%				ON	ON			
SHOW DISCARD	HOLD						OFF		
	DISCARD						ON		
PASSWORD	OFF							OFF	
	ON							ON	
W-UP GAME	NO								OFF
	YES								ON

SW3	LEVEL	1	2	3	4	5	6	7	8
HAND COUNT	NO	OFF							
	YES	ON							
PLAY SCORE	NO		OFF						
	YES		ON						
BOX SCORE	NO			OFF	OFF				
	YES			ON	OFF				
	10 TIMES			OFF	ON				
				ON	ON				

SYSTEM SETUP:

COIN RATE	1,2,4,5,10,15,20,25,40,50,60,75,80,100,200,250,400, 500,1000	
KEY IN RATE		
KETOUT RATE		
TICKET RATE		
GAME TICKET SET	1, 2, 3, 4, 5, 8, 10, CONTINUOUS	CONTINUOUS

PARTS SIDE		SOLDER SIDE
GND	1	GND
GND	2	GND
+ 5V	3	+ 5V
+ 5V	4	+ 5V
+12V	5	+12V
COUNTER POWER	6	
HOPPER CONTROL	7	
	8	
	9	
GND	10	GND

PARTS SIDE		SOLDER SIDE
VIDEO RED	1	VIDEO GREEN
VIDEO BLUE	2	VIDEO SYNC
SPEAKER	3	GND
	4	
	5	
	6	
	7	
	8	
START | 1/2 W-UP	9	
HOLD 1 | SMALL	10	
HOLD 5 | PLAY | 2 W-UP	11	
HOLD 4 | TAKE	12	
HOLD 3 | W-UP	13	
	14	
	15	
HOLD 2 | BIG	16	
	17	
COIN A	18	KEY IN
	19	COIN C
OPERATOR (RECORD)	20	TEST
PAYOUT	21	KEY OUT
	22	TICKET SWITCH
COIN A METER	23	
KEY IN METER	24	
	25	
COIN C METER	26	
OUT METER	27	
	28	
LAMP: START | 1/2 W-UP	29	
LAMP: HOLD 1 | SMALL	30	
LAMP: HOLD 5 | PLAY | 2 W-UP	31	
LAMP: HOLD 4 | TAKE	32	
LAMP: HOLD 3 | W-UP	33	
LAMP: HOLD 2 | BIG	34	
ATTENDANT	35	
GND	36	GND