

Using the set chip to turn on the bill validator on IGT S+ machines

This generally has to be done after the battery has been changed as the default setting is \$.00 or bill off.

1. Turn off power and remove CPU tray
2. Remove the GAME chip and replace it with the set chip.
3. Reinstall the CPU and turn on power.
4. Press the white test switch once the display will read Coin In 0
5. Press the white test switch one more time. The display will read 9-0 or 9-1. Press the spin button til it reads 9-1.
6. Press the white test switch once the display will read Coin In 6 with a 0 in the win. Press the Spin button til the display reads 25 (for Quarters) or what ever number you wish the machine to be.
7. Press the white test switch one more time, the display will read Coin In 0
8. Turn off power and remove CPU tray
9. Remove the Set chip and replace it with the GAME chip.
10. Reinstall the CPU and turn on power.
11. After a short period the display will read 61. Press and hold the test button til 61 changes to 61-1
12. Close and lick the main door. Insert hand pay key into key switch on the side of the machine and turn once. The display should go blank. After about 10 seconds the reels should spin and the machine should be ready to play.